
REVISIONS
ZONE | REV | DESCRIPTION | DATE | E.N.N. NO. | DRAFT | CHKD | APPD
Ø ORIGINAL RELEASE FOR P.R.D. 7/9/61 Ø
LONGHI
LIST OF MATERIAL
THE TECHNICAL MATERIEL CORP.
MAMARONECK, NEW YORK
DIAGRAM, SCHEMATIC (GPR92B)
CK1230
SHEET 3 OF 3
REV. LTR. Ø
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES AND INCLUDE CHEMICALLY APPLIED OR PLATED FINISHES
TOLERANCES
FRACTIONS ±1/64
DECIMALS .X ±.1 .XX ±.03 .XXX ±.005
ANGLES ±1° 30'
CONTINUED FROM SHEET 2
CONTINUED ON SHEET 4
V114 6BA6 4th IF AMPL
V115A 1/2 12AT7 PRODUCT DETECTOR
V115B 1/2 12AT7 BFO
V116 6AB4 BFO ISOL AMPL
V117A 1/2 12AT7 METER AMPL
V117B 1/2 12AX7A AUDIO DRIVER
V118 6AQ5A AUDIO OUTPUT
Z101 BFO ASSY
T102 AUDIO OUTPUT
T101 POWER
T130
S109 FUNCTION
POS 1 AM
POS 2 CW
POS 3 SSB
NOTE: S109 SHOWN IN AM POSITION.
S109A MODE
S109B
S108 LIMITER
S101 AC OFF
S110 RF
P/O E101
LINE
SPEAKER
J107 BFO IN
J103 PHONES
DIODE LOAD
P/O E101
CR105 IN34A AM DETECTOR
CR107 IN34A
CR108 IN463
CR109 IN 463
CR101
M101 M A 0-1
RF ADJ R196 25MEG
VU METER ADJ R210 250K
R200 500 METER ZERO ADJ
+105V INT (SHEET 1)
+105V EXT (SHEET 1)
+250V
AVC
RF GAIN
PHONE LEVEL
R202 500K AUDIO GAIN
R201 500K TONE
R111 47A
R224 1K
R219 22 1W
R218 50
R234 2.2MΩ
R236 220KΩ
R235 2.2M
C298 .001
C299 .001
C300 .01
C266A 20MFD 400V
C266B 20MFD 400V
C256 .003
C255 47
C257 .001
C258 .1
C259 .005
C260 .005
C261 270
C262 25 50V
C263 .02
C264 25 50V
C265 .0015
C267 .005
C268 .2
C269 270
C270 150
C271 .1
C272 .005
C133 .1
C119 2
C122 .1
C101 .1
C102 .1
C120 .203 2KV
C121A 40MFD 350V
C121B 40MFD 350V
R181 100K
R182 47K
R183 1.2K
R189 39K
R180 2.2K 2W
R197 10K
R172 120
R177 33K
R178 3.3K 1W
R179 33K
R190 1.5K
R191 82K
R192 330
R193 10K
R194 1.2K
R198 1.2K
R185 82K 2W
R199 100
R200 500 METER ZERO ADJ
R203 120K
R204 22K
R205 220K 1W
R206 22K
R207 5.6K
R208 220K
R209 270 2W
R211 390K
R212 270 1W
R213 270, 1W
R214 270
R215 47
R216 47
R217 270
R220 47
R221 180K
R222 2.2K
L120 750MH
L118 750MH
L119 750MH
L106
L111 9uh
L109 17uh
L101 6.5H
R101 1W
R103 3K 10W
R102 22, 2W
V101 OB2 VOLTAGE REGULATOR
F101 1.5A/115V .75A/230V
P101
J101
W101
P102
NOTE: FOR 230V OPERATION REMOVE JUMPER *-** AND ADD JUMPER BETWEEN TERMINAL 2 AND SELECTED TERMINAL 3.
NOTE: "S101" IS GANGED TO RF GAIN CONTROL R110 (SEE SHEET 1).
V102 6CB6
V103 6AB4
V104 6BA6
V105 6EW6
V106 6BA7
V107 6AH6
V108 6AU6A
V109 6U8A
V110 6BA6
V111 6AL5
V112 6AZ8
V113 6U8A
V114 6BA6
V115 12AT7
V116 6AB4
V117 12AX7A
V118 6AQ5A
D5101
D5102
D5103
D5104
D5105
TP74
TP75
TP24
TP34
TP44
TP60
TP110
TP88
TP95
TP71-72
NOTES:
1 – TO SHUT OFF LOUDSPEAKER WHEN PHONES ARE INSERTED, CONNECT SPEAKER BETWEEN DESIRED TAP AND G.A. TERMINALS. FOR CONTINUOUS SPEAKER OPERATION WITH PHONES, CONNECT TO DESIRED TAP AND TERMINAL 8 GND.
2 – RESISTANCE VALUES IN OHMS, CAPACITY VALUES IN MICROFARADS AND INDUCTANCE IN MICROHENRIES UNLESS OTHERWISE SPECIFIED.
3 – DENOTES INSULATED SWITCH TERMINALS.
CK-1230 : SP-92B