

TMC SPECIFICATION

NO. S 891

REV:

A

COMPILED:

L. Gabel '74

CHECKED:

APPD:

RJC

SHEET

1

OF

2

TITLE:

CFA-1 to CFA-1L CONVERSION

TMC SPECIFICATION

NO. S 891

REV: A

COMPILED:

CHECKED:

APPD:

SHEET 2 OF 2

TITLE: CFA-1 to CFA-1L CONVERSION

A. To convert a CFA-1 unit to a CFA-1L unit, the following changes must be made to the T5, T6, V6, V7 circuit of the CFA-1.
(REF:CK149, CFA-1 and CK288, CFA-1L.)

1. Add R96 & R97, RC20GF394J
R96 between terminal G1 & G2 of T5.
R97 between terminal G1 & G2 of T6.
 2. Delete R14 (in series with L2).
 3. Delete R28 (in series with L4).
- } Replace with Buss Wire
4. Change C11 & C14 from CM35C113J (.011) to CM30C562J (.0056).
 5. Change R13 & R29 from RC20GF333J to RC20GF474J.
 6. Change R15 & R30 from RC20GF683J to RC20GF474J
 7. Change R94 & R95 from RC20GFG102J to RC20GF121J.
 8. Change C13 & C16 from CM30D242J (.0024) to CM30C402J (.004).

B. All other items in unit are identical.

