WINDING DATA

REQ. PER UNIT	USED ON MODEL	ASS'Y. N.	DATE
2	APP-4		3-14-61
2	APP-5		3-14-61

A-2076 | C

1. WIND 11 TURNS ON 1" O.D. TUBING. LEAVE 5/8 Extending on each end. Use padded Jigs for bends so that coating will not be harmed.
2. Scrape & Tin 1/4" on each end.
3. Test as shown.
4. Assemble and solder Lugs on end, holding 3 1/4" dim, ± 1/16.





SET UP: Touch Solder lightly to each support for measurements.

TEST DATA: [redacted] Test only first coil of each run all remaining Coils may then be passed by Visual Inspection. (Use Boonton "Q" Meter Type 160A or Equivalent).

SPECIFICATIONS
L = 2uhy ± .1uhy
Q = 200 or Greater
F = 7.9 MC

REQ.	ITEM	PART NO.	DESCRIPTION	SYMBOL
X	3	BS-100	Solder, Soft	
2	2	TE-141-3	Terminal, Lug	
X	1	WI-123-10	Wire, Magnet	

ISSUE	ITEM	CHANGED FROM	DATE	CH. NO.	DRAFTS	CHECKER	ENG. APP.
C		COIL ENDS RELOCATED	5.10.67	18196	LFW		FB
B	1	ITEM (1) WAS WI-127-10	6-26-63	9349			
A	1	ON WINDING DATA ITEM 1 WAS CLOSE WIND	4-12-61	4633	W.D.T.		

TOLERANCES
DEC. DIM. ±
FRAC. DIM. ±
ANGULAR DIM. ±

SCALE: DO NOT SCALE

MAXIMUM ALLOWABLE TOLERANCES HAVE BEEN DETERMINED AND ANY DEVIATIONS WILL BE CAUSE FOR REJECTION. REMOVE ALL BURRS AND SHARP EDGES

STOCK SIZE

MATERIAL

TYPE & TEMPER | HEAT TREAT. SPEC.

FINISH & SPEC. NO.

[redacted] TECHNICAL MATERIEL CORP.
MAMARONECK, NEW YORK

CL-269 ASS'Y.

DRAWN	CHECKED	FINAL APPROVAL
D. Millman		Ron Kh
RK		A-2076 C

ELEC. DES. APP | MECH. DES. APP

FORM 108-A